## **SIEMENS**

## **Data sheet**

6ES7134-6HD01-2BA1



SIMATIC ET 200SP, ANALOG INPUT MODULE, AI 4XU/I 2-WIRE STANDARD, PACKING UNIT: 10 PIECES, FITS TO BU-TYPE A0, A1, COLOR CODE CC03, MODULE DIAGNOSIS, 16BIT, +/-0,3%

General information	
Product type designation	Al 4x U/I 2-wire
HW functional status	From FS02
Firmware version	
FW update possible	Yes
usable BaseUnits	BU type A0, A1
Color code for module-specific color identification plate	CC03
Product function	
I&M data	Yes; I&M0 to I&M3
<ul> <li>Isochronous mode</li> </ul>	No
Measuring range scalable	No
Engineering with	
<ul> <li>STEP 7 TIA Portal configurable/integrated from version</li> </ul>	V14 / -
<ul> <li>STEP 7 configurable/integrated from version</li> </ul>	V5.6 and higher
<ul> <li>PCS 7 configurable/integrated from version</li> </ul>	V8.1 SP1
<ul> <li>PROFIBUS from GSD version/GSD revision</li> </ul>	One GSD file each, Revision 3 and 5 and higher
PROFINET from GSD version/GSD revision	GSDML V2.3
Operating mode	
<ul> <li>Oversampling</li> </ul>	No
• MSI	No
CiR - Configuration in RUN	
Reparameterization possible in RUN	Yes
Calibration possible in RUN	No
Supply voltage	
Rated value (DC)	24 V
permissible range, lower limit (DC)	19.2 V
permissible range, upper limit (DC)	28.8 V
Reverse polarity protection	Yes
Input current	
Current consumption, max.	37 mA; without sensor supply
Encoder supply	
24 V encoder supply	
• 24 V	Yes
Short-circuit protection	Yes
<ul> <li>Output current, max.</li> </ul>	20 mA; max. 50 mA per channel for a duration < 10 s
Power loss	
Power loss, typ.	0.85 W; Without encoder supply voltage
Address area	

Address space per module	
Address space per module, max.	8 byte; + 1 byte for QI information
Hardware configuration	o byto, i i byto for an information
Automatic encoding	Yes
Mechanical coding element	Yes
Type of mechanical coding element	Type A
Selection of BaseUnit for connection variants	Tr.
2-wire connection	BU type A0, A1
Analog inputs	
Number of analog inputs	4; Differential inputs
permissible input voltage for voltage input (destruction limit), max.	30 V
permissible input current for current input (destruction limit), max.	50 mA
Cycle time (all channels), min.	Sum of the basic conversion times and additional processing times (depending on the parameterization of the active channels)
Input ranges (rated values), voltages	
• 0 to +10 V	Yes; 15 bit
<ul><li>— Input resistance (0 to 10 V)</li></ul>	120 kΩ
• 1 V to 5 V	Yes; 15 bit
<ul><li>— Input resistance (1 V to 5 V)</li></ul>	120 kΩ
• -10 V to +10 V	Yes; 16 bit incl. sign
— Input resistance (-10 V to +10 V)	120 kΩ
• -5 V to +5 V	Yes; 16 bit incl. sign
— Input resistance (-5 V to +5 V)	120 kΩ
Input ranges (rated values), currents	V - 4719
• 0 to 20 mA	Yes; 15 bit
— Input resistance (0 to 20 mA)	100 Ω; + approx. 0.7 V diode forward voltage
• 4 mA to 20 mA	Yes; 15 bit
— Input resistance (4 mA to 20 mA)	100 Ω; + approx. 0.7 V diode forward voltage
Cable length	4 000 000 f
	THURLES THE MAN TON VOITOGE MAGAZINAMAN
shielded, max.  Analog value generation for the inputs	1 000 m; 200 m for voltage measurement
Analog value generation for the inputs	
Analog value generation for the inputs  Measurement principle	1 000 m; 200 m for voltage measurement integrating (Sigma-Delta)
Analog value generation for the inputs  Measurement principle  Integration and conversion time/resolution per channel	integrating (Sigma-Delta)
Analog value generation for the inputs  Measurement principle  Integration and conversion time/resolution per channel  • Resolution with overrange (bit including sign), max.	integrating (Sigma-Delta)  16 bit
Analog value generation for the inputs  Measurement principle  Integration and conversion time/resolution per channel  • Resolution with overrange (bit including sign), max.  • Integration time, parameterizable	integrating (Sigma-Delta)  16 bit Yes
Analog value generation for the inputs  Measurement principle  Integration and conversion time/resolution per channel  • Resolution with overrange (bit including sign), max.	integrating (Sigma-Delta)  16 bit
Analog value generation for the inputs  Measurement principle  Integration and conversion time/resolution per channel  • Resolution with overrange (bit including sign), max.  • Integration time, parameterizable  • Interference voltage suppression for interference	integrating (Sigma-Delta)  16 bit Yes
Analog value generation for the inputs  Measurement principle  Integration and conversion time/resolution per channel  • Resolution with overrange (bit including sign), max.  • Integration time, parameterizable  • Interference voltage suppression for interference frequency f1 in Hz	integrating (Sigma-Delta)  16 bit Yes 16.6 / 50 / 60 Hz
Analog value generation for the inputs  Measurement principle  Integration and conversion time/resolution per channel  • Resolution with overrange (bit including sign), max.  • Integration time, parameterizable  • Interference voltage suppression for interference frequency f1 in Hz  • Conversion time (per channel)	integrating (Sigma-Delta)  16 bit Yes 16.6 / 50 / 60 Hz
Analog value generation for the inputs  Measurement principle  Integration and conversion time/resolution per channel  • Resolution with overrange (bit including sign), max.  • Integration time, parameterizable  • Interference voltage suppression for interference frequency f1 in Hz  • Conversion time (per channel)  Smoothing of measured values	integrating (Sigma-Delta)  16 bit  Yes  16.6 / 50 / 60 Hz  180 / 60 / 50 ms
Analog value generation for the inputs  Measurement principle  Integration and conversion time/resolution per channel  • Resolution with overrange (bit including sign), max.  • Integration time, parameterizable  • Interference voltage suppression for interference frequency f1 in Hz  • Conversion time (per channel)  Smoothing of measured values  • Number of smoothing levels	integrating (Sigma-Delta)  16 bit Yes 16.6 / 50 / 60 Hz  180 / 60 / 50 ms  4; None; 4/8/16 times
Analog value generation for the inputs  Measurement principle  Integration and conversion time/resolution per channel  • Resolution with overrange (bit including sign), max.  • Integration time, parameterizable  • Interference voltage suppression for interference frequency f1 in Hz  • Conversion time (per channel)  Smoothing of measured values  • Number of smoothing levels  • parameterizable	integrating (Sigma-Delta)  16 bit Yes 16.6 / 50 / 60 Hz  180 / 60 / 50 ms  4; None; 4/8/16 times
Analog value generation for the inputs  Measurement principle  Integration and conversion time/resolution per channel  • Resolution with overrange (bit including sign), max.  • Integration time, parameterizable  • Interference voltage suppression for interference frequency f1 in Hz  • Conversion time (per channel)  Smoothing of measured values  • Number of smoothing levels  • parameterizable  Encoder	integrating (Sigma-Delta)  16 bit Yes 16.6 / 50 / 60 Hz  180 / 60 / 50 ms  4; None; 4/8/16 times
Analog value generation for the inputs  Measurement principle  Integration and conversion time/resolution per channel  • Resolution with overrange (bit including sign), max.  • Integration time, parameterizable  • Interference voltage suppression for interference frequency f1 in Hz  • Conversion time (per channel)  Smoothing of measured values  • Number of smoothing levels  • parameterizable  Encoder  Connection of signal encoders	integrating (Sigma-Delta)  16 bit  Yes  16.6 / 50 / 60 Hz  180 / 60 / 50 ms  4; None; 4/8/16 times  Yes
Analog value generation for the inputs  Measurement principle  Integration and conversion time/resolution per channel  • Resolution with overrange (bit including sign), max.  • Integration time, parameterizable  • Interference voltage suppression for interference frequency f1 in Hz  • Conversion time (per channel)  Smoothing of measured values  • Number of smoothing levels  • parameterizable  Encoder  Connection of signal encoders  • for voltage measurement	integrating (Sigma-Delta)  16 bit Yes 16.6 / 50 / 60 Hz  180 / 60 / 50 ms  4; None; 4/8/16 times Yes
Analog value generation for the inputs  Measurement principle  Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Integration time, parameterizable  Interference voltage suppression for interference frequency f1 in Hz  Conversion time (per channel)  Smoothing of measured values  Number of smoothing levels  parameterizable  Encoder  Connection of signal encoders  for voltage measurement  for current measurement as 2-wire transducer	integrating (Sigma-Delta)  16 bit Yes 16.6 / 50 / 60 Hz  180 / 60 / 50 ms  4; None; 4/8/16 times Yes  Yes
Analog value generation for the inputs  Measurement principle  Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Integration time, parameterizable  Interference voltage suppression for interference frequency f1 in Hz  Conversion time (per channel)  Smoothing of measured values  Number of smoothing levels  parameterizable  Encoder  Connection of signal encoders  for voltage measurement  for current measurement as 2-wire transducer  Burden of 2-wire transmitter, max.	integrating (Sigma-Delta)  16 bit Yes 16.6 / 50 / 60 Hz  180 / 60 / 50 ms  4; None; 4/8/16 times Yes  Yes Yes 650 Ω
Analog value generation for the inputs  Measurement principle  Integration and conversion time/resolution per channel  • Resolution with overrange (bit including sign), max.  • Integration time, parameterizable  • Interference voltage suppression for interference frequency f1 in Hz  • Conversion time (per channel)  Smoothing of measured values  • Number of smoothing levels  • parameterizable  Encoder  Connection of signal encoders  • for voltage measurement  • for current measurement as 2-wire transducer  — Burden of 2-wire transmitter, max.  • for current measurement as 4-wire transducer	integrating (Sigma-Delta)  16 bit Yes 16.6 / 50 / 60 Hz  180 / 60 / 50 ms  4; None; 4/8/16 times Yes  Yes Yes 650 Ω
Analog value generation for the inputs  Measurement principle  Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Integration time, parameterizable  Interference voltage suppression for interference frequency f1 in Hz  Conversion time (per channel)  Smoothing of measured values  Number of smoothing levels  parameterizable  Encoder  Connection of signal encoders  for voltage measurement  for current measurement as 2-wire transducer  Burden of 2-wire transmitter, max.  for current measurement as 4-wire transducer  Errors/accuracies	integrating (Sigma-Delta)  16 bit Yes 16.6 / 50 / 60 Hz  180 / 60 / 50 ms  4; None; 4/8/16 times Yes  Yes 950 Ω No
Analog value generation for the inputs  Measurement principle  Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Integration time, parameterizable  Interference voltage suppression for interference frequency f1 in Hz  Conversion time (per channel)  Smoothing of measured values  Number of smoothing levels  parameterizable  Encoder  Connection of signal encoders  for voltage measurement  for current measurement as 2-wire transducer  Burden of 2-wire transmitter, max.  for current measurement as 4-wire transducer  Errors/accuracies  Linearity error (relative to input range), (+/-)	integrating (Sigma-Delta)  16 bit Yes 16.6 / 50 / 60 Hz  180 / 60 / 50 ms  4; None; 4/8/16 times Yes  Yes 950 Ω No
Analog value generation for the inputs  Measurement principle  Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Integration time, parameterizable  Interference voltage suppression for interference frequency f1 in Hz  Conversion time (per channel)  Smoothing of measured values  Number of smoothing levels  parameterizable  Encoder  Connection of signal encoders  for voltage measurement  for current measurement as 2-wire transducer  Burden of 2-wire transmitter, max.  for current measurement as 4-wire transducer  Errors/accuracies  Linearity error (relative to input range), (+/-)  Temperature error (relative to input range), (+/-)	integrating (Sigma-Delta)  16 bit Yes 16.6 / 50 / 60 Hz  180 / 60 / 50 ms  4; None; 4/8/16 times Yes  Yes Yes 650 Ω No  0.01 % 0.005 %/K
Analog value generation for the inputs  Measurement principle  Integration and conversion time/resolution per channel  • Resolution with overrange (bit including sign), max.  • Integration time, parameterizable  • Interference voltage suppression for interference frequency f1 in Hz  • Conversion time (per channel)  Smoothing of measured values  • Number of smoothing levels  • parameterizable  Encoder  Connection of signal encoders  • for voltage measurement  • for current measurement as 2-wire transducer  — Burden of 2-wire transmitter, max.  • for current measurement as 4-wire transducer  Errors/accuracies  Linearity error (relative to input range), (+/-)  Temperature error (relative to input range), (+/-)  Crosstalk between the inputs, min.  Repeat accuracy in steady state at 25 °C (relative to input	integrating (Sigma-Delta)  16 bit Yes 16.6 / 50 / 60 Hz  180 / 60 / 50 ms  4; None; 4/8/16 times Yes  Yes  Yes 650 Ω No  0.01 % 0.005 %/K 50 dB
Analog value generation for the inputs  Measurement principle  Integration and conversion time/resolution per channel  • Resolution with overrange (bit including sign), max.  • Integration time, parameterizable  • Interference voltage suppression for interference frequency f1 in Hz  • Conversion time (per channel)  Smoothing of measured values  • Number of smoothing levels  • parameterizable  Encoder  Connection of signal encoders  • for voltage measurement  • for current measurement as 2-wire transducer  — Burden of 2-wire transmitter, max.  • for current measurement as 4-wire transducer  Errors/accuracies  Linearity error (relative to input range), (+/-)  Temperature error (relative to input range), (+/-)  Crosstalk between the inputs, min.  Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)	integrating (Sigma-Delta)  16 bit Yes 16.6 / 50 / 60 Hz  180 / 60 / 50 ms  4; None; 4/8/16 times Yes  Yes  Yes 650 Ω No  0.01 % 0.005 %/K 50 dB
Analog value generation for the inputs  Measurement principle  Integration and conversion time/resolution per channel  • Resolution with overrange (bit including sign), max.  • Integration time, parameterizable  • Interference voltage suppression for interference frequency f1 in Hz  • Conversion time (per channel)  Smoothing of measured values  • Number of smoothing levels  • parameterizable  Encoder  Connection of signal encoders  • for voltage measurement  • for current measurement as 2-wire transducer  — Burden of 2-wire transmitter, max.  • for current measurement as 4-wire transducer  Errors/accuracies  Linearity error (relative to input range), (+/-)  Temperature error (relative to input range), (+/-)  Crosstalk between the inputs, min.  Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)  Operational error limit in overall temperature range	integrating (Sigma-Delta)  16 bit Yes 16.6 / 50 / 60 Hz  180 / 60 / 50 ms  4; None; 4/8/16 times Yes  Yes Yes 650 Ω No  0.01 % 0.005 %/K 50 dB 0.05 %
Analog value generation for the inputs  Measurement principle  Integration and conversion time/resolution per channel  Resolution with overrange (bit including sign), max.  Integration time, parameterizable  Interference voltage suppression for interference frequency f1 in Hz  Conversion time (per channel)  Smoothing of measured values  Number of smoothing levels  parameterizable  Encoder  Connection of signal encoders  for voltage measurement  for current measurement as 2-wire transducer  Burden of 2-wire transmitter, max.  for current measurement as 4-wire transducer  Errors/accuracies  Linearity error (relative to input range), (+/-)  Temperature error (relative to input range), (+/-)  Crosstalk between the inputs, min.  Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)  Operational error limit in overall temperature range  Voltage, relative to input range, (+/-)	integrating (Sigma-Delta)  16 bit Yes 16.6 / 50 / 60 Hz  180 / 60 / 50 ms  4; None; 4/8/16 times Yes  Yes Yes 650 Ω No  0.01 % 0.005 %/K 50 dB 0.05 %
Analog value generation for the inputs  Measurement principle  Integration and conversion time/resolution per channel  • Resolution with overrange (bit including sign), max.  • Integration time, parameterizable  • Interference voltage suppression for interference frequency f1 in Hz  • Conversion time (per channel)  Smoothing of measured values  • Number of smoothing levels  • parameterizable  Encoder  Connection of signal encoders  • for voltage measurement  • for current measurement as 2-wire transducer  — Burden of 2-wire transmitter, max.  • for current measurement as 4-wire transducer  Errors/accuracies  Linearity error (relative to input range), (+/-)  Temperature error (relative to input range), (+/-)  Crosstalk between the inputs, min.  Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)  Operational error limit in overall temperature range  • Voltage, relative to input range, (+/-)  • Current, relative to input range, (+/-)	integrating (Sigma-Delta)  16 bit Yes 16.6 / 50 / 60 Hz  180 / 60 / 50 ms  4; None; 4/8/16 times Yes  Yes Yes 650 Ω No  0.01 % 0.005 %/K 50 dB 0.05 %

	:-tf
Interference voltage suppression for f = n x (f1 +/- 1 %), f1 =	
<ul> <li>Series mode interference (peak value of interference &lt; rated value of input range), min.</li> </ul>	70 dB
<ul> <li>Common mode voltage, max.</li> </ul>	10 V
<ul> <li>Common mode interference, min.</li> </ul>	90 dB
Interrupts/diagnostics/status information	
Diagnostics function	Yes
Alarms	
Diagnostic alarm	Yes
Limit value alarm	No
Diagnoses	
<ul> <li>Monitoring the supply voltage</li> </ul>	Yes
<ul><li>Wire-break</li></ul>	Yes; at 4 to 20 mA
Short-circuit	Yes; with 1 to 5 V or 2-wire mode: Short-circuit of the encoder supply to ground or of an input to the encoder supply
Group error	Yes
Overflow/underflow	Yes
Diagnostics indication LED	
<ul> <li>Monitoring of the supply voltage (PWR-LED)</li> </ul>	Yes; green LED
<ul> <li>Channel status display</li> </ul>	Yes; green LED
<ul> <li>for channel diagnostics</li> </ul>	No
<ul> <li>for module diagnostics</li> </ul>	Yes; green/red LED
Potential separation	
Potential separation channels	
• between the channels	Yes; channel group-specific between 2-wire current input group and voltage input group
<ul> <li>between the channels and backplane bus</li> </ul>	Yes
<ul> <li>between the channels and the power supply of the electronics</li> </ul>	Yes; only for voltage inputs
Permissible potential difference	
between the inputs (UCM)	10 V DC
Isolation	
Isolation tested with	707 V DC (type test)
Standards, approvals, certificates	
Suitable for applications according to AMS 2750	Yes; Declaration of Conformity, see online support entry 109757262
Suitable for applications according to CQI-9	Yes
Ambient conditions	
Ambient temperature during operation	
horizontal installation, min.	-30 °C; < 0 °C as of FS02
horizontal installation, max.	60 °C
vertical installation, min.	-30 °C; < 0 °C as of FS02
vertical installation, max.	50 °C
Altitude during operation relating to sea level	
Installation altitude above sea level, max.	5 000 m; Restrictions for installation altitudes > 2 000 m, see manual
Dimensions	
	15 mm
Width	
Width Height	
Height	73 mm
Height Depth	
Height Depth Weights	73 mm 58 mm
Height Depth	73 mm