



SIMATIC S7-1500 analog input module AI 8xU/I/RTD/TC ST, 16 bit resolution, accuracy 0.3%, 8 channels in groups of 8; 4 channels for RTD measurement, common mode voltage 10 V; Diagnostics; Hardware interrupts; Delivery including infeed element, shield bracket and shield terminal: Front connector (screw terminals or push-in) to be ordered separately

General information	
Product type designation	AI 8xU/I/RTD/TC ST
HW functional status	FS04
Firmware version	V2.0.0
<ul style="list-style-type: none"> <li>FW update possible</li> </ul>	Yes
Product function	
<ul style="list-style-type: none"> <li>I&amp;M data</li> </ul>	Yes; I&M0 to I&M3
<ul style="list-style-type: none"> <li>Isochronous mode</li> </ul>	No
<ul style="list-style-type: none"> <li>Prioritized startup</li> </ul>	No
<ul style="list-style-type: none"> <li>Measuring range scalable</li> </ul>	No
<ul style="list-style-type: none"> <li>Scalable measured values</li> </ul>	No
<ul style="list-style-type: none"> <li>Adjustment of measuring range</li> </ul>	No
Engineering with	
<ul style="list-style-type: none"> <li>STEP 7 TIA Portal configurable/integrated from version</li> </ul>	V12 / V12
<ul style="list-style-type: none"> <li>STEP 7 configurable/integrated from version</li> </ul>	V5.5 SP3 / -
<ul style="list-style-type: none"> <li>PROFIBUS from GSD version/GSD revision</li> </ul>	V1.0 / V5.1
<ul style="list-style-type: none"> <li>PROFINET from GSD version/GSD revision</li> </ul>	V2.3 / -
Operating mode	
<ul style="list-style-type: none"> <li>Oversampling</li> </ul>	No
<ul style="list-style-type: none"> <li>MSI</li> </ul>	Yes
CiR - Configuration in RUN	
Reparameterization possible in RUN	Yes
Calibration possible in RUN	Yes
Supply voltage	
Rated value (DC)	24 V
permissible range, lower limit (DC)	19.2 V
permissible range, upper limit (DC)	28.8 V
Reverse polarity protection	Yes
Input current	
Current consumption, max.	240 mA; with 24 V DC supply
Encoder supply	
24 V encoder supply	
<ul style="list-style-type: none"> <li>Short-circuit protection</li> </ul>	Yes
<ul style="list-style-type: none"> <li>Output current, max.</li> </ul>	20 mA; Max. 47 mA per channel for a duration < 10 s
Power	
Power available from the backplane bus	0.7 W
Power loss	
Power loss, typ.	2.7 W
Analog inputs	

Number of analog inputs	8
• For current measurement	8
• For voltage measurement	8
• For resistance/resistance thermometer measurement	4
• For thermocouple measurement	8
permissible input voltage for voltage input (destruction limit), max.	28.8 V
permissible input current for current input (destruction limit), max.	40 mA
Constant measurement current for resistance-type transmitter, typ.	150 Ohm, 300 Ohm, 600 Ohm, Pt100, Pt200, Ni100: 1.25 mA; 6 000 Ohm, Pt500, Pt1000, Ni1000, LG-Ni1000: 0.625 mA; PTC: 0.472 mA
Technical unit for temperature measurement adjustable	Yes; °C/°F/K

**Input ranges (rated values), voltages**

• 0 to +5 V	No
• 0 to +10 V	No
• 1 V to 5 V	Yes
— Input resistance (1 V to 5 V)	100 kΩ
• -1 V to +1 V	Yes
— Input resistance (-1 V to +1 V)	10 MΩ
• -10 V to +10 V	Yes
— Input resistance (-10 V to +10 V)	100 kΩ
• -2.5 V to +2.5 V	Yes
— Input resistance (-2.5 V to +2.5 V)	10 MΩ
• -25 mV to +25 mV	No
• -250 mV to +250 mV	Yes
— Input resistance (-250 mV to +250 mV)	10 MΩ
• -5 V to +5 V	Yes
— Input resistance (-5 V to +5 V)	100 kΩ
• -50 mV to +50 mV	Yes
— Input resistance (-50 mV to +50 mV)	10 MΩ
• -500 mV to +500 mV	Yes
— Input resistance (-500 mV to +500 mV)	10 MΩ
• -80 mV to +80 mV	Yes
— Input resistance (-80 mV to +80 mV)	10 MΩ

**Input ranges (rated values), currents**

• 0 to 20 mA	Yes
— Input resistance (0 to 20 mA)	25 Ω; Plus approx. 42 ohms for overvoltage protection by PTC
• -20 mA to +20 mA	Yes
— Input resistance (-20 mA to +20 mA)	25 Ω; Plus approx. 42 ohms for overvoltage protection by PTC
• 4 mA to 20 mA	Yes
— Input resistance (4 mA to 20 mA)	25 Ω; Plus approx. 42 ohms for overvoltage protection by PTC

**Input ranges (rated values), thermocouples**

• Type B	Yes
— Input resistance (Type B)	10 MΩ
• Type C	No
• Type E	Yes
— Input resistance (Type E)	10 MΩ
• Type J	Yes
— Input resistance (type J)	10 MΩ
• Type K	Yes
— Input resistance (Type K)	10 MΩ
• Type L	No
• Type N	Yes
— Input resistance (Type N)	10 MΩ
• Type R	Yes
— Input resistance (Type R)	10 MΩ
• Type S	Yes
— Input resistance (Type S)	10 MΩ
• Type T	Yes
— Input resistance (Type T)	10 MΩ
• Type TXK/TXK(L) to GOST	No

**Input ranges (rated values), resistance thermometer**

• Cu 10	No
• Cu 10 according to GOST	No

• Cu 50	No
• Cu 50 according to GOST	No
• Cu 100	No
• Cu 100 according to GOST	No
• Ni 10	No
• Ni 10 according to GOST	No
• Ni 100	Yes; Standard/climate
— Input resistance (Ni 100)	10 MΩ
• Ni 100 according to GOST	No
• Ni 1000	Yes; Standard/climate
— Input resistance (Ni 1000)	10 MΩ
• Ni 1000 according to GOST	No
• LG-Ni 1000	Yes; Standard/climate
— Input resistance (LG-Ni 1000)	10 MΩ
• Ni 120	No
• Ni 120 according to GOST	No
• Ni 200 according to GOST	No
• Ni 500	No
• Ni 500 according to GOST	No
• Pt 10	No
• Pt 10 according to GOST	No
• Pt 50	No
• Pt 50 according to GOST	No
• Pt 100	Yes; Standard/climate
— Input resistance (Pt 100)	10 MΩ
• Pt 100 according to GOST	No
• Pt 1000	Yes; Standard/climate
— Input resistance (Pt 1000)	10 MΩ
• Pt 1000 according to GOST	No
• Pt 200	Yes; Standard/climate
— Input resistance (Pt 200)	10 MΩ
• Pt 200 according to GOST	No
• Pt 500	Yes; Standard/climate
— Input resistance (Pt 500)	10 MΩ
• Pt 500 according to GOST	No
<b>Input ranges (rated values), resistors</b>	
• 0 to 150 ohms	Yes
— Input resistance (0 to 150 ohms)	10 MΩ
• 0 to 300 ohms	Yes
— Input resistance (0 to 300 ohms)	10 MΩ
• 0 to 600 ohms	Yes
— Input resistance (0 to 600 ohms)	10 MΩ
• 0 to 3000 ohms	No
• 0 to 6000 ohms	Yes
— Input resistance (0 to 6000 ohms)	10 MΩ
• PTC	Yes
— Input resistance (PTC)	10 MΩ
<b>Thermocouple (TC)</b>	
<b>Temperature compensation</b>	
— parameterizable	Yes
— internal temperature compensation	Yes
— external temperature compensation via RTD	Yes
— Compensation for 0 °C reference point temperature	Yes; fixed value can be set
— Reference channel of the module	Yes
<b>Cable length</b>	
• shielded, max.	800 m; for U/I, 200 m for R/RTD, 50 m for TC
<b>Analog value generation for the inputs</b>	
<b>Integration and conversion time/resolution per channel</b>	
• Resolution with overrange (bit including sign), max.	16 bit
• Integration time, parameterizable	Yes
• Integration time (ms)	2,5 / 16,67 / 20 / 100 ms
• Basic conversion time, including integration time (ms)	9 / 23 / 27 / 107 ms

<ul style="list-style-type: none"> <li>— additional conversion time for wire-break monitoring</li> <li>— additional conversion time for resistance measurement</li> <li>• Interference voltage suppression for interference frequency <math>f_1</math> in Hz</li> <li>• Time for offset calibration (per module)</li> </ul>	<p>9 ms (to be considered in R/RTD/TC measurement)</p> <p>150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm, Pt500, Pt1000, Ni1000, LG-Ni1000, PTC: 4 ms</p> <p>400 / 60 / 50 / 10 Hz</p> <p>Basic conversion time of the slowest channel</p>
<b>Smoothing of measured values</b>	
<ul style="list-style-type: none"> <li>• parameterizable</li> <li>• Step: None</li> <li>• Step: low</li> <li>• Step: Medium</li> <li>• Step: High</li> </ul>	<p>Yes</p> <p>Yes</p> <p>Yes</p> <p>Yes</p> <p>Yes</p>
<b>Encoder</b>	
<b>Connection of signal encoders</b>	
<ul style="list-style-type: none"> <li>• for voltage measurement</li> <li>• for current measurement as 2-wire transducer <ul style="list-style-type: none"> <li>— Burden of 2-wire transmitter, max.</li> </ul> </li> <li>• for current measurement as 4-wire transducer</li> <li>• for resistance measurement with two-wire connection</li> <li>• for resistance measurement with three-wire connection</li> <li>• for resistance measurement with four-wire connection</li> </ul>	<p>Yes</p> <p>Yes</p> <p>820 <math>\Omega</math></p> <p>Yes</p> <p>Yes; Only for PTC</p> <p>Yes; All measuring ranges except PTC; internal compensation of the cable resistances</p> <p>Yes; All measuring ranges except PTC</p>
<b>Errors/accuracies</b>	
Linearity error (relative to input range), (+/-)	0.02 %
Temperature error (relative to input range), (+/-)	0.005 %/K; With TC type T 0.02 $\pm$ % / K
Crosstalk between the inputs, max.	-80 dB
Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)	0.02 %
Temperature error of internal compensation	$\pm 6$ °C
<b>Operational error limit in overall temperature range</b>	
<ul style="list-style-type: none"> <li>• Voltage, relative to input range, (+/-)</li> <li>• Current, relative to input range, (+/-)</li> <li>• Resistance, relative to input range, (+/-)</li> <li>• Resistance thermometer, relative to input range, (+/-)</li> <li>• Thermocouple, relative to input range, (+/-)</li> </ul>	<p>0.3 %</p> <p>0.3 %</p> <p>0.3 %</p> <p>Ptxxx standard: <math>\pm 1.5</math> K, Ptxxx climate: <math>\pm 0.5</math> K, Nixxx standard: <math>\pm 0.5</math> K, Nixxx climate: <math>\pm 0.3</math> K</p> <p>Type B: <math>&gt; 600</math> °C <math>\pm 4.6</math> K, type E: <math>&gt; -200</math> °C <math>\pm 1.5</math> K, type J: <math>&gt; -210</math> °C <math>\pm 1.9</math> K, type K: <math>&gt; -200</math> °C <math>\pm 2.4</math> K, type N: <math>&gt; -200</math> °C <math>\pm 2.9</math> K, type R: <math>&gt; 0</math> °C <math>\pm 4.7</math> K, type S: <math>&gt; 0</math> °C <math>\pm 4.6</math> K, type T: <math>&gt; -200</math> °C <math>\pm 2.4</math> K</p>
<b>Basic error limit (operational limit at 25 °C)</b>	
<ul style="list-style-type: none"> <li>• Voltage, relative to input range, (+/-)</li> <li>• Current, relative to input range, (+/-)</li> <li>• Resistance, relative to input range, (+/-)</li> <li>• Resistance thermometer, relative to input range, (+/-)</li> <li>• Thermocouple, relative to input range, (+/-)</li> </ul>	<p>0.1 %</p> <p>0.1 %</p> <p>0.1 %</p> <p>Ptxxx standard: <math>\pm 0.7</math> K, Ptxxx climate: <math>\pm 0.2</math> K, Nixxx standard: <math>\pm 0.3</math> K, Nixxx climate: <math>\pm 0.15</math> K</p> <p>Type B: <math>&gt; 600</math> °C <math>\pm 1.7</math> K, type E: <math>&gt; -200</math> °C <math>\pm 0.7</math> K, type J: <math>&gt; -210</math> °C <math>\pm 0.8</math> K, type K: <math>&gt; -200</math> °C <math>\pm 1.2</math> K, type N: <math>&gt; -200</math> °C <math>\pm 1.2</math> K, type R: <math>&gt; 0</math> °C <math>\pm 1.9</math> K, type S: <math>&gt; 0</math> °C <math>\pm 1.9</math> K, type T: <math>&gt; -200</math> °C <math>\pm 0.8</math> K</p>
<b>Interference voltage suppression for <math>f = n \times (f_1 \pm 1 \%)</math>, <math>f_1</math> = interference frequency</b>	
<ul style="list-style-type: none"> <li>• Series mode interference (peak value of interference &lt; rated value of input range), min.</li> <li>• Common mode voltage, max.</li> <li>• Common mode interference, min.</li> </ul>	<p>40 dB</p> <p>10 V</p> <p>60 dB</p>
<b>Interrupts/diagnostics/status information</b>	
Diagnostics function	Yes
<b>Alarms</b>	
<ul style="list-style-type: none"> <li>• Diagnostic alarm</li> <li>• Limit value alarm</li> </ul>	<p>Yes</p> <p>Yes; two upper and two lower limit values in each case</p>
<b>Diagnoses</b>	
<ul style="list-style-type: none"> <li>• Monitoring the supply voltage</li> <li>• Wire-break</li> <li>• Overflow/underflow</li> </ul>	<p>Yes</p> <p>Yes; Only for 1 to 5 V, 4 to 20 mA, TC, R, and RTD</p> <p>Yes</p>
<b>Diagnostics indication LED</b>	
<ul style="list-style-type: none"> <li>• RUN LED</li> </ul>	Yes; green LED

<ul style="list-style-type: none"> <li>• ERROR LED</li> <li>• Monitoring of the supply voltage (PWR-LED)</li> <li>• Channel status display</li> <li>• for channel diagnostics</li> <li>• for module diagnostics</li> </ul>	Yes; red LED Yes; green LED Yes; green LED Yes; red LED Yes; red LED
<b>Potential separation</b>	
Potential separation channels	
<ul style="list-style-type: none"> <li>• between the channels</li> <li>• between the channels, in groups of</li> <li>• between the channels and backplane bus</li> <li>• between the channels and the power supply of the electronics</li> </ul>	No 8 Yes Yes
<b>Permissible potential difference</b>	
between the inputs (UCM)	20 V DC
Between the inputs and MANA (UCM)	10 V DC
<b>Isolation</b>	
Isolation tested with	707 V DC (type test)
<b>Standards, approvals, certificates</b>	
Suitable for applications according to AMS 2750	Yes; Declaration of Conformity, see online support entry 109757262
Suitable for applications according to CQI-9	Yes; Based on AMS 2750 E
<b>Ambient conditions</b>	
Ambient temperature during operation	
<ul style="list-style-type: none"> <li>• horizontal installation, min.</li> <li>• horizontal installation, max.</li> <li>• vertical installation, min.</li> <li>• vertical installation, max.</li> </ul>	0 °C 60 °C 0 °C 40 °C
Altitude during operation relating to sea level	
<ul style="list-style-type: none"> <li>• Installation altitude above sea level, max.</li> </ul>	5 000 m; Restrictions for installation altitudes > 2 000 m, see manual
<b>Dimensions</b>	
Width	35 mm
Height	147 mm
Depth	129 mm
<b>Weights</b>	
Weight, approx.	310 g
<b>Other</b>	
Note:	Additional basic error and noise for integration time = 2.5 ms: Voltage: $\pm 250$ mV ( $\pm 0.02\%$ ), $\pm 80$ mV ( $\pm 0.05\%$ ), $\pm 50$ mV ( $\pm 0.05\%$ ); resistance: 150 ohms $\pm 0.02\%$ ; resistance thermometer: Pt100 climate: $\pm 0.08$ K, Ni100 climate: $\pm 0.08$ K; thermocouple: Type B, R, S: $\pm 3$ K, type E, J, K, N, T: $\pm 1$ K
last modified:	4/29/2021 