Data sheet 6ES7522-1BL10-0AA0



SIMATIC S7-1500, digital output module, DQ32xDC 24V/0.5A BA, 32 channels in groups of 8, 4 A per group; the module supports the safety-oriented shutdown of load groups up to SIL2 according to EN IEC 62061:2021 and Category 3 / PL d according to EN ISO 13849-1:2015. delivery incl. front connector push-in

General information		
Product type designation	DQ 32x24VDC/0.5A BA	
HW functional status	From FS01	
Firmware version	V1.0.0	
 FW update possible 	Yes	
Product function		
	Yes; I&M0 to I&M3	
 Isochronous mode 	No	
Prioritized startup	Yes	
Engineering with		
 STEP 7 TIA Portal configurable/integrated from version 	V13 / V13	
 STEP 7 configurable/integrated from version 	V5.5 SP3 / -	
 PROFIBUS from GSD version/GSD revision 	V1.0 / V5.1	
 PROFINET from GSD version/GSD revision 	V2.3 / -	
Operating mode		
• DQ	Yes	
 DQ with energy-saving function 	No	
• PWM	No	
 Oversampling 	No	
• MSO	Yes	
Supply voltage		
Rated value (DC)	24 V	
permissible range, lower limit (DC)	19.2 V	
permissible range, upper limit (DC)	28.8 V	
Reverse polarity protection	Yes; through internal protection with 7 A per group	
Input current		
Current consumption, max.	60 mA	
output voltage / header		
Rated value (DC)	24 V	
Power		
Power available from the backplane bus	1.15 W	
Power loss		
Power loss, typ.	3.8 W	
Digital outputs		
Type of digital output	Transistor	
Number of digital outputs	32	
Current-sourcing	Yes	
Digital outputs, parameterizable	No	
Short-circuit protection	Yes	
 Response threshold, typ. 	1 A	

Limitation of inductive shutdown voltage to	L+ (-53 V)
Controlling a digital input	Yes
Switching capacity of the outputs	
 with resistive load, max. 	0.5 A
on lamp load, max.	5 W
Load resistance range	
• lower limit	48 Ω
upper limit	12 kΩ
Output voltage	
• for signal "1", min.	L+ (-0.8 V)
Output current	
for signal "1" rated value	0.5 A
• for signal "1" permissible range, max.	0.5 A
for signal "0" residual current, max.	0.5 mA
Output delay with resistive load	
• "0" to "1", max.	100 μs
• "1" to "0", max.	500 μs
Parallel switching of two outputs	
• for logic links	Yes
• for uprating	No
for redundant control of a load	Yes
Switching frequency	
with resistive load, max.	100 Hz
with inductive load, max.	0.5 Hz; According to IEC 60947-5-1, DC-13
• on lamp load, max.	10 Hz
Total current of the outputs	
Current per channel, max.	0.5 A; see additional description in the manual
Current per group, max.	4 A; see additional description in the manual
Current per module, max.	16 A; see additional description in the manual
Cable length	10 7 4 500 additional accompliant in the management
shielded, max.	1 000 m
unshielded, max.	600 m
Interrupts/diagnostics/status information	
Diagnostics function	No
Substitute values connectable	No
Alarms	140
Diagnostic alarm	No
Diagnostic alaim	
-	
Maintenance interrupt	No
Maintenance interrupt Diagnoses	No
 Maintenance interrupt Diagnoses Monitoring the supply voltage 	No No
 Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break 	No No No
Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit	No No No
Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Group error	No No No
Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Group error Diagnostics indication LED	No No No No
Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Group error Diagnostics indication LED RUN LED	No No No No No No Yes; green LED
Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Group error Diagnostics indication LED RUN LED ERROR LED	No No No No No Yes; green LED Yes; red LED
Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Group error Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED)	No No No No Yes; green LED Yes; red LED Yes; green LED
Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Group error Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display	No No No No No Yes; green LED Yes; green LED Yes; green LED Yes; green LED
Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Group error Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics	No No No No No Ves; green LED Yes; green LED Yes; green LED Yes; green LED No
Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Group error Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics	No No No No No Yes; green LED Yes; green LED Yes; green LED Yes; green LED
Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Group error Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics Potential separation	No No No No No Ves; green LED Yes; green LED Yes; green LED Yes; green LED No
Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Group error Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics Potential separation Potential separation channels	No No No No Ves; green LED Yes; green LED Yes; green LED Yes; green LED No No No
Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Group error Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics Potential separation Potential separation channels between the channels	No No No No No Yes; green LED Yes; green LED Yes; green LED No No No
Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Group error Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics Potential separation Potential separation channels	No No No No Ves; green LED Yes; green LED Yes; green LED Yes; green LED No No No
Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Group error Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics Potential separation Potential separation channels between the channels, in groups of between the channels and backplane bus	No No No No No Yes; green LED Yes; green LED Yes; green LED No No No
Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Group error Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics Potential separation Potential separation channels between the channels, in groups of	No No No No No Ves; green LED Yes; green LED Yes; green LED No No No No
Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Group error Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics Potential separation Potential separation channels between the channels, in groups of between the channels and backplane bus	No No No No No Ves; green LED Yes; green LED Yes; green LED No No No No
Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Group error Diagnostics indication LED RUN LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics for module diagnostics between the channels between the channels between the channels and backplane bus	No No No No Ves; green LED Yes; green LED Yes; green LED Yes; green LED No No No No
Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Group error Diagnostics indication LED RUN LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics for module diagnostics between the channels between the channels, in groups of between the channels and backplane bus	No No No No Ves; green LED Yes; green LED Yes; green LED Yes; green LED No No No No
Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Group error Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics Potential separation Potential separation channels between the channels between the channels and backplane bus Isolation Isolation tested with Standards, approvals, certificates	No No No No No Ves; green LED Yes; red LED Yes; green LED Yes; green LED No No No No No No No No No No No No N

Highest safety class achievable for safety-related tripping of standard modules	
 Performance level according to ISO 13849-1 	PL d
 Category according to ISO 13849-1 	Cat. 3
 SIL acc. to IEC 62061 	SIL 2
 remark on safety-oriented shutdown 	https://support.industry.siemens.com/cs/de/de/view/39198632
Ambient conditions	
Ambient temperature during operation	
 horizontal installation, min. 	-30 °C; from FS04
 horizontal installation, max. 	60 °C
 vertical installation, min. 	-30 °C; from FS04
 vertical installation, max. 	40 °C
Altitude during operation relating to sea level	
 Installation altitude above sea level, max. 	5 000 m; Restrictions for installation altitudes > 2 000 m, see manual
Dimensions	
Width	25 mm
Height	147 mm
Depth	129 mm
Weights	
Weight, approx.	280 g
Other	
Note:	Supplied incl. 40-pole push-in front connectors

last modified:

5/6/2022