

MLFB-Ordering data

6SL3210-5BE32-2CV0



Figure similar

Client order no. : Order no. : Offer no. : Remarks : Item no. : Consignment no. : Project :

Rated data					
Input					
Number of phases	3 AC				
Line voltage	380 480 V -15 % +10 %				
Line frequency	47 63 Hz				
Output					
Normal are of what are	2.46				

	300 100 1 10 %
Line frequency	47 63 Hz
Dutput	
Number of phases	3 AC
Rated voltage	400 V
Rated power (HO)	22.00 kW / 30.00 hp
Rated power (LO)	30.00 kW / 40.00 hp
Rated current (HO)	45.00 A
Rated current (LO)	60.00 A
Rated current (HO) at 480V	40.00 A
Rated current (LO) at 480V	52.00 A
Pulse frequency	4.00 kHz
Output frequency	0 550 Hz

General tech. specifications					
Power factor λ	0.72				
Offset factor cos φ	0.95				
Efficiency η	0.98				
Filter class (integrated)	Class A				
Ambient conditions					
Cooling	External fan				
Installation altitude	1000 m (3281 ft)				
Ambient temperature					
Operation	-10 60 °C (14 140 °F)				
Storage	-40 70 °C (-40 158 °F)				
Relative humidity					
Max. operation	95 %				
Communication					

**Standards** 

Low Overload (LO)

110 % rated output current for 60 s, cycle time 300 s

High Overload (HO)

150 % rated output current for 60 s, cycle time 300 s

Communication

**CE** marking

Compliance with standards

USS, Modbus RTU

61800-3

CE, cULus, C-Tick (RCM), KC

EN 61800-5-1 /EN 60204-1 and EN



## **MLFB-Ordering data**

**Analog outputs** 

Number

6SL3210-5BE32-2CV0



Figure similar

Mechanical data		Connections		
Mounting position  Through-hole moun side-by-side moun		hole mounting / wall mounting /	Max. motor cable length	l
		ide mounting	Shielded	50 m (164 ft)
Degree of protection	IP20 / UL	open type	Unshielded 100 m (32	
Size	FSE			
Net weight	6.99 kg ( 15.41 lb )			
Width	245.0 mr	m ( 9.65 in )		
Height	264.5 mr	m ( 10.41 in )		
Depth	209.0 mr	m ( 8.23 in )		
Inputs / outputs				
Standard digital inputs				
Number		4		
Digital outputs				
Number as relay changeov	er contact	1		
Number as transistor		1		
Analog inputs				
Number		2 (Can be used as additional digital input)		